



MHG GRINDER USE & CARE INSTRUCTIONS

COFFEE GRINDING



STEP 1

Visually inspect the hoppers for an ample supply of whole bean coffee.



STEP 2

Place a paper filter into the brew funnel. The filter must not be folded over or tilted to one side. Insert the funnel into the funnel rails and push until it stops.



STEP 3

Choose the batch size and side of grinder to use. It is not necessary to select a size on the brewer.



STEP 4

Momentarily press and release the **GRIND** button. The grinding action will stop automatically after the preset amount of ground coffee is dispensed into the funnel. Pressing the **STOP** button will terminate a grind.



STEP 5

Remove the funnel from the grinder and level the bed of grounds by gently shaking. The loaded funnel is now ready for use in any commercial drip coffee brewer according to the manufacturer's instructions.

BUNN®

CLEANING

MHG GRINDER USE & CARE INSTRUCTIONS



STEP 1

Empty all beans from hopper(s). Plug in the grinder, place funnel with filter into funnel rails. Press and release the **GRIND** button. Run a few cycles until all coffee in the grind chamber is dispensed and disconnect the grinder from the power source.



STEP 2

Remove the funnel with filter and discard any remaining coffee grounds.



STEP 3

Remove the hoppers by sliding all the way forward.



STEP 4

Remove the hopper lid from the hopper.



STEP 5

Clean and sanitize the hoppers and lids. Care should be taken not to scratch the hoppers with any abrasive material.

NOTE: Bunn-O-Matic recommends the 3 step method for cleaning and sanitizing the server. The 3 step method consists of hot soapy water using an approved detergent, a fresh water rinse, and an aqueous sanitizing solution using an approved **non-chlorine** sanitizer.



STEP 6

Clean all exterior surfaces using a damp cloth rinsed in any mild, nonabrasive, liquid detergent.



STEP 7

Replace the hoppers and fill with fresh whole bean coffee. Replace the hopper lids.