

Remote Pairing the My Turn Systems

To use up to 3 (or more) different remotes with a single My Turn queue management system display at the same time, you need to pair each remote to the same channel code (C1–C8).

Instructions for Pairing Multiple Remotes:

1. **Activate Programming Mode:** On a remote, press all three buttons simultaneously until the red LED light turns on.
2. **Select Communication Code:** Keep the buttons pressed until the LED switches off. Upon release, the controller will flash 1 to 8 times, corresponding to the current communication channel (1-8).
3. **Set the Channel:** While the LED is flashing, press the "Feed" button (middle button) to choose the desired channel (e.g., C1). Ensure all 3 remotes are set to the *same* channel number.
4. **Pair with Display:** Press the button on top of the display unit. The display will show the current code (e.g., C1) and wait 5 seconds.
5. **Confirm Pairing:** Press the central button on the remote. The display will update to the remote's code, confirming the pairing.
6. **Repeat:** Repeat steps 1–5 for the other two remotes, ensuring they are set to the same channel as the first.