

Heated Display Case

Start-Up Checklist



Before Initial Use

Before the initial use of the display case, heat the display case—without pans—to burn off any residual surface oils.

To do so:

1. Remove pans from display case.
2. Set the bottom heater switch [1] to the "ON" position.
3. Set bottom thermostats [2] to the "10" setting.
3. Set top thermostats [4] to the "10" setting.
4. Allow the display case to heat for 30 minutes or until no odor is detected.

Before Start-Up

- ☐ Record serial and model number
- ☐ Have customer register the appliance

On-Site

- ☐ Remove all packaging
- ☐ Install all glass panels
- ☐ Clean glass
- ☐ Wipe out bottom of deli pan with soapy water. Wipe with water and dry (do not pour water into deli pan)
- ☐ Arrange divider bars as desired (for well-style units) Consult manual for suggested configurations (pull plastic coating off bars)
- ☐ Clean and Install optional cutting board and/or scale shelf (as applicable)
- ☐ Plug in or have appliance hardwired by an electrician (as applicable)
- ☐ Preheat the appliance on setting 10 for up to 20 minutes with pans
- ☐ Place hot food into the case and reduce temperature to appropriate temperature for the food items being held hot

CONTACT INFORMATION

Alto-Shaam Service 1-800-558-8744 ext 12345

Name _____

Phone _____

Serial number is required for all inquiries.

Always include both model and serial numbers in any correspondence regarding the appliance.

Model _____

Serial Number _____

Purchased From _____

Date Installed _____

CONTACT US

W164 N9221 Water Street | Menomonee Falls, Wisconsin 53051 | U.S.A.
Phone: 262.251.3800 | 800.558.8744 U.S.A./Canada | Fax: 262.251.7067 | alto-shaam.com