



Project _____

Item 6952RCBORC Quantity _____

Approval _____ Date _____

Lavex Remote Capable Red LED Exit Sign / Emergency Light Combo with Adjustable Arrows and Ni-Cad Battery Backup - 4.2 Watt Unit (2W Remote Capacity)

Item #6952RCBORC

Special Features

- (2) 1.2W light heads with red LED exit sign (2W Remote Capacity)
- Universal J box mounting system with mounting hardware included
- UL 94V-0 flame rating; lasts 90 minutes after power failure with maintenance free batteries
- Lights up hallways and entrances in case of emergency
- 120V/277V operation with a 9.6V back-up NiCad battery; push button to test

Technical Data

Width	19 1/2 Inches
Depth	2 1/8 Inches
Height	7 15/16 Inches
Voltage	120/277 Volts
Battery Life	90 Minutes
Battery Type	NiCad Battery
Color	White
DC Voltage	9.6 Volts
Housing Type	Flame Retardant Thermoplastic




Certifications



UL Certified

Technical Data

Features	Battery Backup Directional Chevron Remote Capable
Language	English
Lettering Color	Red
Number of Faces	2 Faces
Ratings	cULus NFPA Compliant
Type	Exit Sign Combo Signs
Unit Wattage	4.2 Watts

 **WARNING:** This product can expose you to chemicals including lead, which are known to the State of California to cause cancer and birth defects or other reproductive harm. For more information, go to www.p65warnings.ca.gov.